

U14 decoupling Cap 100nF U2J // 100uF polymer.
Use 2 pieces of copper tape to connect from pin 7 and pin 14 of U14 to the 2 components accross mounted the U14
C94 is U14 Original decoupling Cap 100nF
U15 and U33 are Clock switches. Mount 100nF // 47uF polymer SMD or Black gate HQx across
U34 are Output buffer for SPDIF mount 100nF U2J // 100uF polymer SMD or similar as shown
(Black gate 47uF HQx is used on photo)
Replace original E cal 33uF with 100uF polymer SMD or similar as shown